



Help-Lite emergency sign with alarm indicator, reset module and pull switch



HELP legend is visible when activated

Help-Lite SR10

The Help-Lite is designed for the less able person. It is suited to disabled toilets or similar compartments in Hospitals, Care Homes, Educational Facilities, Sheltered Accommodation or similar facilities.

The SR10-65M has been engineered with an IP65 enclosure and has a state of the art battery back-up in the event of a mains failure.

- HELP legend – visible when activated
- High pitched sounder to get attention
- Pull switch activation
- Reset module with reassurance indicator
- Remote alarm indicator for warden’s office
- Operates in mains failure
- Ingress rated luminaire for outdoor fitting

SPECIFICATION

ELECTRICAL & OPERATIONAL	SELF-CONTAINED
Input voltage	230 – 240v 50Hz
Duration	At mains failure up to 2 hours on standby battery
Lamp	8wT5
Lamp o/p (lumens)	400

CONSTRUCTION & INSTALLATION

Cable entry	Luminaire: rear end moulded locations, 20mm
Construction	Luminaire: High-grade polycarbonate plastic body in white. Clear PC optically engineered diffuser. Remote alarm and reset units are incorporated into pattress fascias
Environment	0 – 25°C
Ingress class	IP65
Dimensions lwd (mm)	Luminaire: 343 x 98 x 73
Weight (kg)	2 (pack)

TO ORDER

STANDARD ORDER CODE	DESCRIPTION
SR10-65M – PACK	Help-Lite pack, complete with IP65 rated luminaire, ‘HELP’ legend panel, remote alarm pattress mounted module, reset module, and emergency pull cord unit with red cord and handle pull

SPARES		OPTIONS	
SR11-ALM	Alarm unit	VRKIT	Security screw fixing kit
SR11-RES	Reset unit	XTR	Semi-recess trim bezel with fixing bracket